


TUCK




TUCK

	W	K	Lm	Colour	L1 x L2 x L3	
30250104	10W	4000K	800	Matt Black	130 x 90 x 35 mm	1/20
30260104	10W	4000K	800	Matt White	130 x 90 x 35 mm	1/20
30250204	20W	4000K	1600	Matt Black	180 x 126 x 36 mm	1/10
30260204	20W	4000K	1600	Matt White	180 x 126 x 36 mm	1/10
30250304	30W	4000K	2400	Matt Black	210 x 147 x 37 mm	1/10
30260304	30W	4000K	2400	Matt White	210 x 147 x 37 mm	1/10
30250504	50W	4000K	4000	Matt Black	260 x 182 x 41 mm	1/6
30260504	50W	4000K	4000	Matt White	260 x 182 x 41 mm	1/6



220-240 V
50-60 Hz



TUCK SENSOR



TUCK Sensor

		W	K	Lm	Colour	L1 x L2 x L3	
30360304		30W	4000K	2400	Matt Black	210 x 147 x 37 mm	1/10
30370304		30W	4000K	2400	Matt White	210 x 147 x 37 mm	1/10



220-240 V
50-60 Hz



SENSOR



65



> 0,9



NO DIM



> 15.000




50.000 h.



120°



DRIVER INCL



ACCESSORY

30360000	Tuck Remote Control · Mando a distancia	1


- Controla tus TUCK SENSOR con un solo mando
- Control your TUCK SENSOR with one single remote control
- Contrôlez vos TUCK SENSOR avec une seule télécommande
- Controlla il tuo TUCK SENSOR con un solo telecomando
- Steuern Sie Ihre TUCK SENSOR mit einer einzigen Fernbedienung

MAT ALU

SENSOR



SENSIBILIDAD/SENSITIVITY/SENSIBILITÉ/SENSIBILITÀ/SENSIBILITÄT




100%: 7-8 m
 75%: 5-6 m
 50%: 3-4 m
 25%: 1-2 m

TIEMPO/TIME/TEMPS/TEMPO/ZEITEN



Duración hasta el apagado:
 Duration time to light off:
 Durée jusqu'à l'éteigne:
 Durata fino al spento:
 Dauer bis zur Abschaltung:
 Min: 5 sec
 Max: 24 h

MODO/MODE/MODE/MODALITÀ/MODUS



Modo día: El sensor funciona de día y de noche.
Daylight Mode: The sensor work both in day and night.
Mode Jour: Le détecteur fonctionne jour et nuit.
Modalità Giorno: Il sensore funziona giorno e notte.
Tag-Modus: Der Sensor funktioniert Tag und Nacht.



Modo Crepuscular: La luminaria se enciende automáticamente de noche, <50lux
Photocell Mode: The luminary lights on automatic in night, <50lux
Mode Crépusculaire : Le luminaire s'allume automatiquement la nuit, <50lux
Modalità Crepuscolo: Il apparecchio è acceso automaticamente durante la notte, <50lux
Dämmerungs-Modus: Die Leuchte schaltet sich Nachts automatisch ein, <50lux



Modo Manual: La luminaria está siempre encendida.
Manuel Override Mode: Keep light on all the time.
Mode manuel: Le luminaire est toujours allumé.
Modalità Manuale: Il apparecchio è sempre acceso.
Manueller Modus: Die Leuchte ist immer eingeschaltet.



Modo SOS.
SOS Mode.
Mode SOS.
Modalità SOS.
Modus SOS.



Modo Noche: El sensor sólo funciona de noche, <50lux
Nightlight Mode: The sensor work only in night, <50lux
Mode Nuit : Le détecteur fonctionne que la nuit, <50lux
Modalità Notte: Il sensore funziona soltanto di notte, <50lux
Nacht-Modus: Der Sensor funktioniert nur Nachts, <50lux



Sin Función.
Meanless Function.
Sans Fonction.
Senza Funzione.
Ohne Funktion.



Modo Flash.
Flash Mode.
Mode Flash.
Modalità Flash.
Modus Flash.



Modo Apagado.
OFF Mode.
Mode OFF.
Modalità OFF.
Modus OFF.

